



# Thinvent Aero Mini PC

## Intel Core i5-1335U processor

10 core, up to 4.6 GHz, 12 MB cache

## 4GB DDR4 RAM

## 1TB SSD

## Dual Band WiFi

## Windows 11 Pro

SKU: AERO-I5\_13-4-M1024-12\_5-M-11P-0



### Experience Mighty Performance in a Miniature Package.

Unleash the power of the Thinvent® Aero Mini PC, engineered for efficiency and performance in an ultra-compact design. Powered by the Intel® Core™ i5-1335U processor, featuring 10 cores and clocking up to 4.6 GHz with a 12 MB cache, this mini PC effortlessly handles demanding tasks and ensures a lag-free experience.

#### Seamless Multitasking & Blazing Speed

- Enjoy smooth operations with 16GB DDR4 RAM, perfect for intensive applications.
- Boot up instantly and load applications in a flash thanks to the 128GB SSD.
- Work securely and productively with pre-installed Windows 11 Pro, offering advanced features and robust security.

#### Extensive Connectivity & Versatility

- Connect multiple displays with 1 HDMI and 1 VGA port for enhanced productivity.

- Access a total of 8 USB ports, including 2 high-speed USB 3.2, 6 USB 2.0 (4 conveniently located on the front), and a versatile front USB C port for all your peripherals.
- Experience ultra-fast networking with 1000 Mbps Ethernet and dual-band Wi-Fi 5 (802.11ac) for reliable wireless connectivity.
- Integrated audio with front and rear speaker out/mic in ensures comprehensive multimedia support.

#### Compact Design, Robust Build

- Measuring just 198mm x 187mm x 40mm, it fits seamlessly into any workspace, from offices to home setups.
- Constructed from durable steel and ABS plastic with a sleek, powder-coated black finish for lasting reliability.
- Certified by BIS, RoHS, and ISO, guaranteeing quality and safety standards.

The Thinvent® Aero Mini PC is your ideal solution for professional productivity, home office efficiency, and versatile computing, delivering powerful performance without compromise.



## Specifications

### PROCESSING

---

Generation	13th
Series	i5
Processor Brand	Intel
Processor Model	1335U
Cores	10
Max Frequency	4.6 GHz
Cache	12 MB
Main Memory	4 GB
SSD Storage	1024 GB

### DISPLAY

---

HDMI	1
VGA	1

### AUDIO

---

Speaker Out	1
Mic In	1
Front Speaker Out	1
Front Mic In	1

### CONNECTIVITY

---

USB 3.2	2
USB 2.0	2
Front USB 2.0	4
Front USB C	1

### NETWORKING

---

Ethernet	1000 Mbps
Wireless Networking	Wi-Fi 5 (802.11ac), dual band

### POWER

---

DC Voltage	12 Volts
DC Current	5 Amps
Power Input	100~240 Volts AC, 50~60 Hz, 1.5 Amps maximum
Cable Length	2 Metre

### ENVIRONMENTAL

---

Operating Temperature	0°C ~ 35°C
Operating Humidity	20% ~ 80% RH, non condensing
Certifications	BIS, RoHS, ISO

### PHYSICAL

---

Form Factor	Mini PC
Dimensions	198mm × 187mm × 40mm
Housing Material	Steel and ABS Plastic
Housing Finish	Powder Coated
Housing Colour	Black
Net and Gross Weight	1.51kg, 1.51kg

### OPERATING SYSTEM

---

Operating System	Microsoft Windows 11 Pro
------------------	--------------------------

## Ordering Information

PRODUCT CODE	
<b>Aero-i5_13-[RAM]-[SSD]-12_7-[Wireless]-[OS]-[Accessories]</b>	
<b>RAM</b>	<b>4</b> = 4GB DDR4 <b>8</b> = 8GB DDR4 <b>16</b> = 16GB DDR4 <b>32</b> = 32GB DDR4 <b>64</b> = 64GB DDR4
<b>SSD</b>	<b>m128</b> = 128GB <b>m256</b> = 256GB <b>m32</b> = 32GB <b>m512</b> = 512GB <b>m1024</b> = 1TB <b>S32</b> = 32GB MLC <b>S128</b> = 128GB <b>S256</b> = 256GB
<b>Wireless</b>	<b>m</b> = Dual Band WiFi <b>X</b> = No WiFi
<b>OS</b>	<b>DOS</b> = DOS <b>W_OS</b> = Without OS <b>11V</b> = Windows 11 IoT Value <b>11P</b> = Windows 11 Pro <b>Thinix</b> = Thinix™ Embedded Linux <b>U</b> = Ubuntu Linux
<b>Accessories</b>	<b>0</b> = None <b>KM</b> = Keyboard and Mouse set <b>MK</b> = Mechanical Keyboard <b>Mo</b> = Wired Optical Scroll Mouse

[www.thinvent.in](http://www.thinvent.in)

[sales@thinvent.in](mailto:sales@thinvent.in)

+91-11-430-77467

+91-99903-44251

### R&D and Manufacturing

#11 Sports Complex  
 Salvador Do Mundo  
 North Goa - 403101, India

### Sales

UGF-10-A Omaxe Gurgaon Mall  
 Sector 49, Sohna Road  
 Gurgaon - 122018, India

