



# Thinvent Neo R/4 Mini PC

## Intel Core 5 120U processor

10 core, up to 5.0 GHz, 12 MB cache

## 32GB DDR4 RAM

## 256GB SSD

## Dual Band WiFi

## Windows 11 Pro

SKU: R-I5\_14-32-M256-12\_5-M-11P-0



Unleash Mighty Performance in a Mini Footprint.

Experience the perfect blend of power, precision, and portability with the Thinvent® Neo R/4 Mini PC. Engineered for demanding tasks, this compact powerhouse redefines efficiency for your home or business.

### Unrivaled Performance

- Harness the exceptional processing prowess of the Intel® Core™ 5 120U processor, featuring 10 cores and bursting up to 5.0 GHz with a 12 MB cache for seamless multitasking and lightning-fast responsiveness.
- Multitask effortlessly with 16GB DDR4 RAM.
- Enjoy instant boot-ups and rapid application loading thanks to the swift 256GB SSD.
- Elevate your productivity and security with the pre-installed Microsoft Windows 11 Pro.

### Comprehensive Connectivity

- Drive up to three displays simultaneously with 2 HDMI and 1 VGA port, expanding your visual workspace.
- Stay connected with reliable dual-band Wi-Fi 5 (802.11ac) and a blazing 1000 Mbps Ethernet port.

- Connect all your peripherals with 2 USB 3.0 and 2 USB 2.0 ports.
- Integrate your audio setup seamlessly with dedicated speaker out and mic in jacks.

### Compact & Robust Design

- Revolutionize your workspace with its incredibly compact dimensions of 198mm x 200mm x 73mm and a featherlight weight of just 110 grams.
- Built to last, its durable steel housing with a sleek black powder coating ensures longevity and a professional aesthetic.
- Designed for continuous operation, it performs reliably across an operating temperature range of 0°C to 40°C and 20% to 80% RH non-condensing humidity.
- Trust in its quality, backed by BIS, RoHS, and ISO certifications.

### Efficient Power

- Powered by a stable 12V 7A adapter, compatible with a wide 100~275V AC input range.



# Thinvent Neo R/4 Mini PC



## Specifications

### PROCESSING

---

Generation	14th
Series	i5
Processor Brand	Intel
Processor Model	120U
Cores	10
Max Frequency	5 GHz
Cache	12 MB
Main Memory	32 GB
SSD Storage	256 GB

### DISPLAY

---

HDMI	2
VGA	1

### AUDIO

---

Speaker Out	1
Mic In	1

### CONNECTIVITY

---

USB 3.0	2
USB 2.0	2

### NETWORKING

---

Ethernet	1000 Mbps
Wireless Networking	Wi-Fi 5 (802.11ac), dual band

### POWER

---

DC Voltage	12 Volts
DC Current	5 Amps
Power Input	100~240 Volts AC, 50~60 Hz, 1.5 Amps maximum
Cable Length	2 Metre

### ENVIRONMENTAL

---

Operating Temperature	0°C ~ 40°C
Operating Humidity	20% ~ 80% RH, non condensing
Certifications	BIS, RoHS, ISO

### PHYSICAL

---

Form Factor	Mini PC
Dimensions	198mm × 200mm × 73mm
Packing Dimensions	340mm × 235mm × 105mm
Weight	110 grams
Housing Material	Steel
Housing Finish	Powder Coated
Housing Colour	Black
Net and Gross Weight	1.23kg, 1.65kg

### OPERATING SYSTEM

---

Operating System	Microsoft Windows 11 Pro
------------------	--------------------------

## Ordering Information

PRODUCT CODE			
<b>R-i5_14-[RAM]-[SSD]-12_7-[Wireless]-[OS]-[Accessories]</b>			
<b>RAM</b>	<b>4</b> = 4GB DDR4 <b>64</b> = 64GB DDR4	<b>8</b> = 8GB DDR4	<b>16</b> = 16GB DDR4 <b>32</b> = 32GB DDR4
<b>SSD</b>	<b>m128</b> = 128GB <b>m32</b> = 32GB <b>m1024</b> = 1TB <b>S128</b> = 128GB		<b>m256</b> = 256GB <b>m512</b> = 512GB <b>S32</b> = 32GB MLC <b>S256</b> = 256GB
<b>Wireless</b>	<b>m</b> = Dual Band WiFi		<b>X</b> = No WiFi
<b>OS</b>	<b>DOS</b> = DOS <b>11V</b> = Windows 11 IoT Value <b>Thinix</b> = Thinix™ Embedded Linux		<b>W_OS</b> = Without OS <b>11P</b> = Windows 11 Pro <b>U</b> = Ubuntu Linux
<b>Accessories</b>	<b>0</b> = None <b>1S</b> = DB9 Serial <b>Mo</b> = Wired Optical Scroll Mouse		<b>KM</b> = Keyboard and Mouse set <b>MK</b> = Mechanical Keyboard

[www.thinvent.in](http://www.thinvent.in)

[sales@thinvent.in](mailto:sales@thinvent.in)

+91-11-430-77467

+91-99903-44251

**R&D and Manufacturing**  
#11 Sports Complex  
Salvador Do Mundo  
North Goa - 403101, India

**Sales**  
UGF-10-A Omaxe Gurgaon Mall  
Sector 49, Sohna Road  
Gurgaon - 122018, India

