



# Thinvent Neo R/4 Mini PC

## Intel Core i7-1255U processor

10 core, up to 4.7 GHz, 12 MB cache

## Dual LAN

## 16GB DDR4 RAM

## 256GB SSD

## No WiFi

## Thinux Embedded Linux

## Thinvent Keyboard and Mouse set



SKU: R-I7\_12L-16-M256-12\_7-X-THINUX-KM

Unlock Uncompromising Industrial Performance: The Thinvent Neo R/4 Mini PC.

The ultimate digital engine for demanding industrial applications, built for reliability and seamless integration where it matters most.

### Engineered for Reliability

- Unshakeable performance in harsh or space-constrained environments, from factory floors to digital signage installations.
- Purpose-built for 24/7 operation, ensuring your critical processes and displays never miss a beat.
- Rugged, compact steel construction provides robust protection and effortless mounting virtually anywhere.

### Streamlined Control and Deployment

- Out-of-the-box readiness with our pre-installed Thinux™ Embedded OS, designed for stability and ease of management.

- Remotely configure, monitor, and troubleshoot your entire fleet of devices from a single, intuitive browser-based dashboard.
- Dual Ethernet ports offer enhanced network flexibility and redundancy for mission-critical connectivity.

### Powering Your Digital Vision

- Effortlessly drives complex industrial HMIs, interactive kiosks, and multi-screen digital signage with smooth, responsive visuals.
- A trusted cornerstone for secure, dedicated control systems in automation, manufacturing, and smart building management.
- The complete package includes our reliable keyboard and mouse set, so you can deploy and go live immediately.



## Specifications

### PROCESSING

---

Generation	12th
Series	i7
Processor Brand	Intel
Processor Model	1255U
Cores	10
Max Frequency	4.7 GHz
Cache	12 MB
Main Memory	16 GB
SSD Storage	256 GB

### DISPLAY

---

HDMI	1
VGA	1

### AUDIO

---

Speaker Out	1
Mic In	1

### CONNECTIVITY

---

USB 3.2	2
RS485 Option	1

### NETWORKING

---

Ethernet	1000 Mbps
Ethernet Ports	2

### POWER

---

DC Voltage	12 Volts
DC Current	7 Amps
Power Input	100~275 Volts AC, 50~60 Hz, 1.5 Amps maximum
Cable Length	2 Metre

### ENVIRONMENTAL

---

Operating Temperature	0°C ~ 40°C
Operating Humidity	20% ~ 80% RH, non condensing
Certifications	BIS, RoHS, ISO

### PHYSICAL

---

Form Factor	Mini PC
Dimensions	198mm × 200mm × 73mm
Packing Dimensions	340mm × 235mm × 105mm
Weight	110 grams
Housing Material	Steel
Housing Finish	Powder Coated
Housing Colour	Black
Net and Gross Weight	2.23kg, 2.65kg

### ACCESSORIES

---

Keyboard and Mouse	1
--------------------	---

### OPERATING SYSTEM

---

Operating System	Thinvent® Thinux™ Embedded Linux
OS Features	Chromium and Mozilla Firefox browsers. RDP 10 (RemoteFX, H.264/AVC), Putty and SSH for remote display. Browser based remote management. VNC shadowing. Java, Python and glibc based location application support. LibreOffice and PDF viewer. Multimedia player with MPEG4 support. SIP video and voice over IP.



## Ordering Information

PRODUCT CODE	
<b>R-i7_12l-[RAM]-[SSD]-12_7-[Wireless]-[OS]-[Accessories]</b>	
<b>RAM</b>	<b>4</b> = 4GB DDR4 <b>8</b> = 8GB DDR4 <b>16</b> = 16GB DDR4 <b>32</b> = 32GB DDR4 <b>64</b> = 64GB DDR4
<b>SSD</b>	<b>m128</b> = 128GB <b>m256</b> = 256GB <b>m32</b> = 32GB <b>m512</b> = 512GB <b>m1024</b> = 1TB <b>S32</b> = 32GB MLC <b>S128</b> = 128GB <b>S256</b> = 256GB
<b>Wireless</b>	<b>m</b> = Dual Band WiFi <b>X</b> = No WiFi
<b>OS</b>	<b>DOS</b> = DOS <b>W_OS</b> = Without OS <b>11V</b> = Windows 11 IoT Value <b>11P</b> = Windows 11 Pro <b>Thinix</b> = Thinix™ Embedded Linux <b>U</b> = Ubuntu Linux
<b>Accessories</b>	<b>0</b> = None <b>KM</b> = Keyboard and Mouse set <b>1S</b> = DB9 Serial <b>MK</b> = Mechanical Keyboard <b>Mo</b> = Wired Optical Scroll Mouse

[www.thinvent.in](http://www.thinvent.in)

[sales@thinvent.in](mailto:sales@thinvent.in)

+91-11-430-77467

+91-99903-44251

**R&D and Manufacturing**  
 #11 Sports Complex  
 Salvador Do Mundo  
 North Goa - 403101, India

**Sales**  
 UGF-10-A Omaxe Gurgaon Mall  
 Sector 49, Sohna Road  
 Gurgaon - 122018, India

