



Thinvent® Neo S Thin Client, Intel® processor J4125 (4 core, up to 2.7 GHz, 4 MB cache), 4GB DDR4 RAM, 128GB SSD + 32 GB MLC SSD, 19V 1.3A Adapter, No WiFi, Ubuntu Linux

SKU: S-G-4-m128_S32-19_1-X-U-0

Engineered for Resilience, Made for India: The Thinvent Neo S.



Processing

| | |
|---------------|---------|
| Cores | 4 |
| Max Frequency | 2.7 GHz |
| Cache | 4 MB |
| Main Memory | 4 GB |
| SSD Storage | 32 GB |

Display

| | |
|------|---|
| HDMI | 1 |
| VGA | 1 |

Audio

| | |
|-------------|---|
| Speaker Out | 1 |
| Mic In | 1 |

Connectivity

| | |
|---------------|-------------------------|
| USB 3.2 Gen 1 | 4 |
| USB 2.0 | 2 |
| Serial Port | 2 DB9 male RS232 |
| Parallel Port | 1 DB25 female IEEE 1284 |

Networking

| | |
|----------|-----------|
| Ethernet | 1000 Mbps |
|----------|-----------|

Power

| | |
|--------------|---|
| DC Voltage | 19 Volts |
| DC Current | 1.3 Amps |
| Power Input | 100~280 Volts AC, 50 Hz, 0.7 Amps maximum |
| Cable Length | 1.8 Metre |

Environmental

| | |
|-----------------------|------------------------------|
| Operating Temperature | 0°C ~ 40°C |
| Operating Humidity | 20% ~ 80% RH, non condensing |
| Certifications | BIS, RoHS, ISO |

Physical

| | |
|------------------|--------------------------|
| Dimensions | 204mm × 186.5mm × 53.5mm |
| Housing Material | Steel |
| Housing Finish | Power Coating |
| Housing Colour | Black |

Operating System

| | |
|------------------|------------------------|
| Operating System | Ubuntu Linux 24.04 LTS |
|------------------|------------------------|