



# Thinvent Uno 23.8" All in One PC

## Intel Core i5-1335U processor

10 core, up to 4.6 GHz, 12 MB cache

## 8GB DDR4 RAM

## 128GB SSD

## Dual Band WiFi

## Without OS

## Height Adjustable Stand

SKU: UNO24-I5\_13-8-M128-12\_10-M-W\_OS-HA



## Experience Seamless Productivity with the Thinvent® Uno All in One PC

Unleash your potential with the Thinvent® Uno 23.8" All in One PC, a sleek and powerful solution designed for modern workspaces. This elegant machine combines robust performance with a minimalist aesthetic, perfect for any home or office environment.

### Key Performance Features

- Powered by an Intel® Core™ i5-1335U processor, featuring 10 cores that reach up to 4.6 GHz with a 12 MB cache for lightning-fast multitasking.
- Enjoy smooth operation and quick application loading with 8 GB DDR4 RAM.
- Store all your important files and applications with ample space on the 512 GB SSD.

### Stunning Visuals and Immersive Experience

- A brilliant 23.8-inch Full HD (1920 × 1080) display with 250 nits brightness delivers crisp visuals.
- Experience true-to-life colors and clarity from any angle with 178° horizontal and vertical viewing angles.

- The integrated 2 Megapixel pop-up camera ensures clear video conferencing.
- Integrated 2 × 3 Watts speakers provide clear audio.

### Versatile Connectivity and Design

- Connect all your essential peripherals with a comprehensive range of ports, including HDMI, VGA, USB 3.2 (2), USB 2.0 (2), and side USB 2.0 (2).
- Enjoy blazing-fast network speeds with 1000 Mbps Ethernet and dual-band Wi-Fi 5 (802.11ac).
- The included height-adjustable stand allows for personalized ergonomic comfort.
- Built with a premium aluminum alloy, steel, and ABS plastic housing in a sophisticated black finish.
- Secure your device with a built-in Kensington Lock.

Please note: This model comes Without OS, allowing you the freedom to install your preferred operating system.



# Thinvent Uno 23.8" All in One PC



## Specifications

### PROCESSING

---

Generation	13th
Series	i5
Processor Brand	Intel
Processor Model	1335U
Cores	10
Max Frequency	4.6 GHz
Cache	12 MB
Main Memory	8 GB
SSD Storage	128 GB

### DISPLAY

---

Screen Size	23.8 inch
Resolution	1920 × 1080
Brightness	250 nits
Viewing Angle	Horizontal 178°, Vertical 178°
Camera	Pop up, 2 Megapixel
HDMI	1
VGA	1

### AUDIO

---

Speakers	2 × 3 Watts
Speaker Out	1
Mic In	1

### CONNECTIVITY

---

USB 3.2	2
USB 2.0	2
Side USB 2.0	2

### NETWORKING

---

Ethernet	1000 Mbps
Wireless Networking	Wi-Fi 5 (802.11ac), dual band

### POWER

---

DC Voltage	12 Volts
DC Current	10 Amps
Power Input	100~275 Volts AC, 50~60 Hz, 1.5 Amps maximum
Cable Length	2 Metre

### ENVIRONMENTAL

---

Operating Temperature	0°C ~ 35°C
Operating Humidity	20% ~ 80% RH, non condensing
Certifications	BIS, RoHS, ISO

### PHYSICAL

---

Form Factor	All-in-One
Stand	Height Adjustable
Dimensions	541mm × 400mm × 55mm
Housing Material	Aluminium alloy, steel and ABS Plastic
Housing Colour	Black
Kensington Lock	Yes
Net and Gross Weight	8.42kg, 8.42kg

### OPERATING SYSTEM

---

Operating System	Without OS
------------------	------------

## Ordering Information

PRODUCT CODE				
<b>Uno24-i5_13-[RAM]-[SSD]-12_10-[Wireless]-[OS]-[Accessories]</b>				
RAM	<b>4</b> = 4GB DDR4	<b>8</b> = 8GB DDR4	<b>16</b> = 16GB DDR4	<b>32</b> = 32GB DDR4
	<b>64</b> = 64GB DDR4			
SSD	<b>m128</b> = 128GB		<b>m256</b> = 256GB	
	<b>m32</b> = 32GB		<b>m512</b> = 512GB	
	<b>m1024</b> = 1TB			
Wireless	<b>m</b> = Dual Band WiFi		<b>X</b> = No WiFi	
OS	<b>DOS</b> = DOS		<b>W_OS</b> = Without OS	
	<b>11V</b> = Windows 11 IoT Value		<b>11P</b> = Windows 11 Pro	
	<b>Thinix</b> = Thinix™ Embedded Linux		<b>U</b> = Ubuntu Linux	
Accessories	<b>F</b> = Fixed Stand		<b>HA</b> = Height Adjustable Stand	

[www.thinvent.in](http://www.thinvent.in)

[sales@thinvent.in](mailto:sales@thinvent.in)

+91-11-430-77467

+91-99903-44251

**R&D and Manufacturing**  
 #11 Sports Complex  
 Salvador Do Mundo  
 North Goa - 403101, India

**Sales**  
 UGF-10-A Omaxe Gurgaon Mall  
 Sector 49, Sohna Road  
 Gurgaon - 122018, India

